

Homework Assignment #4: Chap. 7

Due: April 23, 2020

I Program Assignment (50%)

1. (10%) Determine DFS coefficients of the following periodic sequences:
 - (a) $\tilde{x}[n] = 2 \cos(\pi n/4)$
 - (b) $\tilde{x}[n] = 3 \sin(0.25\pi n) + 4\cos(0.75\pi n)$

2. (10%) Let $x[n]$ be an N -point sequence with an N -point DFT $X[k]$.
 - (a) If N is even and if $x[n] = -x[\langle n + N/2 \rangle_N]$ for all n , then show that $X[k] = 0$ for even k .
 - (b) Show that if $N=4m$ where m is an integer and if $x[n] = -x[\langle n + N/4 \rangle_N]$ for all n , then $X[k]=0$ for $k = 4\ell$, $0 \leq \ell \leq \frac{N}{4} - 1$

3. (12%) Let $x_1[n], 0 \leq n \leq N_1 - 1$, be an N_1 -point sequence and let $x_2[n], 0 \leq n \leq N_2 - 1$, be an N_2 -point sequence. Let $x_3[n] = x_1[n] * x_2[n]$ and let $x_4[n] = x_1[n] \otimes x_2[n]$, $N \geq \max(N_1, N_2)$
 - (a) Show that
$$x_4[n] = \sum_{l=-\infty}^{\infty} x_3[n + lN] \tag{7.209}$$
 - (b) Let $e[n] = x_4[n] - x_3[n]$, show that
$$e[n] = \begin{cases} x_3[n + N], & \max(N_1, N_2) \leq N < L \\ 0, & N \geq L \end{cases}$$
where $L = N_1 + N_2 - 1$
 - (c) Verify the results in (a) and (b) for $x_1 = \{1_{n=0, 2, 3, 4}\}$, $x_2 = \{4_{n=0, 3, 2, 1}\}$, and $N=5$ and $N=8$

4. (8%) Let $\tilde{x}[n]$ be a periodic sequence with fundamental period N and let $\tilde{X}[k]$ be its DFS. Let $\tilde{x}_3[n]$ be periodic with period $3N$ consisting of three periods of $\tilde{x}[n]$ and let $\tilde{X}_3[k]$ be its DFS. Determine $\tilde{X}_3[k]$ in terms of $\tilde{X}[k]$.

5. (10%) The first five values of the 9-point DFT of a real-valued sequence $x[n]$ are given by

$$\{4, 2 - j3, 3 + j2, -4 + j6, 8 - j7\}$$

Without computing IDFT and then DFT but using DFT properties only, determine the DFT of each of the following sequences:

- (a) $x_1[n] = x[\langle n + 2 \rangle_9]$
- (b) $x_2[n] = 2x[\langle 2 - n \rangle_9]$
- (c) $x_3[n] = x[n] \otimes x[\langle -n \rangle_9]$
- (d) $x_4[n] = x^2[n]$
- (e) $x_5[n] = x[n]e^{-j4\pi n/9}$

II Program Assignment (50%)

1. (8%) Let $x[n] = n(0.9)^n u[n]$,
 - (a) Determine the DTFT $\tilde{X}(e^{j\omega})$ of $x[n]$. **Please write your calculations and answer on your .mlx file.**
 - (b) Choose first $N = 20$ samples of $x[n]$ and compute the approximate DTFT $\tilde{X}_N(e^{j\omega})$ using the `fft` function. Plot magnitudes of $\tilde{X}(e^{j\omega})$ and $\tilde{X}_N(e^{j\omega})$ in one plot and compare your results.
 - (c) Repeat part (b) using $N = 50$.
 - (d) Repeat part (b) using $N = 100$.

2. (10%) Let $x[n] = x_1[n] + jx_2[n]$ where sequences $x_1[n]$ and $x_2[n]$ are real-valued.
 - (a) Show that $X_1[k] = X^{cce}[k]$ and $jX_2[k] = X^{cco}[k]$. **Please write your calculations and answer on your .mlx file.**
 - (b) Write a MATLAB function `[X1,X2] = tworealDFTs(x1,x2)` that implements the results in part (a).
 - (c) Verify your function on the following two sequences: $x_1[n] = 0.9^n$, $x_2[n] = (1 - 0.8^n)$; $0 \leq n \leq 49$

3. (9%) Let $x_1[n] = \{1_{n=0}, 2, 3, 4, 5\}$ be a 5-point sequence and let $x_2[n] = \{2_{n=0}, -1, 1, -1\}$ be a 4-point sequence.
 - (a) Determine $x_1[n] \otimes x_2[n]$ using hand calculations. **Please write your calculations and**

answer on your .mlx file.

- (b) Verify your calculations in (a) using the `circconv` function.
- (c) Verify your calculations in (a) by computing the DFTs and IDFT.

4. (8%) Let $x_1[n]$ be an N_1 -point and $x_2[n]$ be an N_2 -point sequence. Let $N \geq \max(N_1, N_2)$. Their N -point circular convolution is shown to be equal to the aliased version of their linear convolution in (7.209) in **Program Assignment 3**. This result can be used to compute the circular convolution via the linear convolution.

- (a) Develop a MATLAB function

`y = lin2circconv(x,h)`

that implements this approach.

- (b) For $x[n] = \{1_{n=0}, 2, 3, 4\}$ and $h[n] = \{1_{n=0}, -1, 1, -1\}$ determine their 4-point circular convolution using the `lin2circconv` function and verify using the `circconv` function.

5. (15%) Let a 2D filter impulse response $h[m, n]$ be given by

$$h[m, n] = \begin{cases} \frac{1}{2\pi\sigma^2} e^{-\frac{m^2+n^2}{2\sigma^2}} & , -128 \leq m, n \leq 127 \\ 0 & , otherwise \end{cases}$$

where σ is a parameter. For this problem use the “Lena” image.

- (a) For $\sigma = 4$, determine $h[m, n]$ and compute its 2D-DFT $H[k, l]$ via the `fft2` function taking care of shifting the origin of the array from the middle to the beginning (using the `fftshift` function). Show the log-magnitude of $H[k, l]$ as an image.
- (b) Process the “Lena” image in the frequency domain using the above $H[k, l]$. This will involve taking 2D-DFT of the image, multiplying the two DFTs and then taking the inverse of the product. Comment on the visual quality of the resulting filtered image.
- (c) Repeat (a) and (b) for $\sigma = 32$ and comment on the resulting filtered image as well as the difference between the two filtered images.
- (d) The filtered image in part (c) also suffers from an additional distortion due to a spatial-domain aliasing effect in the circular convolution. To eliminate this artifact, consider both the image and the filter $h[m, n]$ as 512×512 size images using zero-padding in each dimension. Now perform the frequency-domain filtering and comment on the resulting filtered image.
- (e) Repeat part (b) for $\sigma = 4$ but now using the frequency response $1 - H[k, l]$ for the filtering. Compare the resulting filtered image with that in (b).